

AccSens Plus for 32 doors Stand Alone Proximity Controller



REAL TIME FOR 32 DOORS

- *Restricted Access*
- *Barriers*
- *Industrial Doors*
- *Gates*
- *Turnstiles*

Provides a total control of up to 32 independent access points and 6000 users without the requirement of a personal computer or expensive software.

Allows for real-time serial printing of all transaction, with a memory buffer of 500 date/time stamped transactions, consisting of 32 zones.

FEATURES

- Capable of interfacing with various reader technology.
- One internal reading and facility for connection of 32 nodes a RS485 network.
- Read 64 bit. Manchester code (EM4002) proximity cards.
- Relay output is provided to control electric door strikes or magnetic locks.
- Alarm relay output for door monitoring function.
- 2 Inputs for free-exit function and door monitoring.
- Programming by means of four membrane buttons – ESC, Enter, ←and→.
- 32 character back-lit display.
- Full voiding facility for all 6000 users
- Versatile anti-pass back facility between various combinations of readers.
- User zoning and time capability.
- Can be connected to a series printer or printer to monitor system events

SPECIFICATIONS

INPUT POWER SUPPLY	9-16V DC - 200mA
OUTPUT POWER SUPPLY	2m
RELAY OUTPUT	2 Relays with a change-over contacts. Rating - 3A @ 24V AC/DC
SOLID STATE INPUT	2 Solid State inputs
FREQUENCY/ CODING	125kHz/ Manchester (EM4002)
USER CAPACITY	2000 (including Master Tags)
DISPLAY	2 Line, 32 character, back-lit
RESPONSE	Buzzer
PROGRAMMING	ESC, ENTER, ←and→.
COMMUNICATION	RS485 – Bi-Directional network comms. Maximum 8 nodes. RS232 – Serial printer/ terminal comms. Buffer – 500 transactions

PLEASE CONTACT OUR SALES TEAM +27 31 700 8099 for further information.

PART OF THE MARANTEC COMPANY GROUP
OPENING DOORS IN SOUTH AFRICA
PROUD SUPPORTERS AND SUPPLIERS OF



PROTECTION CATEGORY	Internal Use only
DIMENSIONS	150mm (W) x 100mm (L) x 26mm (D)
MASS	250 grams
OPERATING TEMPERATURE	-5°C to +50°C
HUMIDITY RANGE	5 to 95% RH, non-condensing.
OPERATION	<p>Security settings - Select High, Med, Low</p> <p>Add new users - 2 possible modes; Including Multiple Master cards</p> <p>Edit users - Edit access rights</p> <p>Voiding - Full voiding facilities</p> <p>Zoning - 32 user groups with time zones</p> <p>Door Setting - Add doors, Remove doors and set access times</p> <p>Relay Times - Setting of relay output time</p> <p>Anti-passback - Configurable between any combination of reading heads</p> <p>Set Time - Setting up of time, day, month and year</p>

(The Company reserves the right to amend product specifications and information without notice.)

PLEASE CONTACT OUR SALES TEAM +27 31 700 8099 for further information.

**PART OF THE MARANTEC COMPANY GROUP
 OPENING DOORS IN SOUTH AFRICA
 PROUD SUPPORTERS AND SUPPLIERS OF**

